

CM-1110 Managed Media and Rate Converters Module

10/100/1000Base-T to 1000Base-X Conversion



- 10/100/1000Base-T to 1000Base-X Fiber Media Converters
- Connect 10/100 devices to Gigabit backbone
- Extend network distances up to 160km
- Advanced features - Smart Link Pass-Through, Fiber Fault Alert, Auto-MDIX and Loopback
- High density applications with **Perle Media Converter Chassis**
- Manage via SNMP, CLI - Telnet/SSH, Internet browser, or **PerleVIEW Central Management Platform** with an **MCR-MGT Media Converter Management Module**

Installed in a high density **Perle Media Converter Chassis**, Perle's line of feature rich **Managed 10/100/1000 Rate Converting Media Converters** transparently connect copper to fiber. Our 10/100/1000 Ethernet to Fiber Converters provide an economical path to extend the distance of an existing network, the life of non-fiber based equipment, or the distance between two devices.

Network Administrators can "see-everything" with Perle's advanced features such as Auto-Negotiation, Auto-MDIX, **Link Pass-Through**, Fiber Fault Alert, and Loopback. Along with a **Media Converter Management Module** in the chassis, configuration and monitoring of the copper and fiber ports can be performed. These cost and time saving features, along with a lifetime warranty and free worldwide technical support, make Perle's **Managed 10/100/1000 Media Converter Modules** the smart choice for IT professionals.

For those environments requiring a medium to large-scale deployment of media converters, a centralized platform that simplifies the configuration, administration, monitoring, and troubleshooting of this gear is recommended. **PerleVIEW Device Management** software is a multi-user, Windows server-based application that delivers this level of Enterprise-grade solution.

CM-1110 Managed Media Converter Features

QOS (Quality of Service)

- Bandwidth Allocation via rate limiting
 - IEEE 802.1P tagged frame priority control
 - IEEE 802.1P priority tag remapping
 - IP TOS (Type of Service) priority for IPV4 Diffserv or IPV6 traffic class frames
 - Congestion Service Policy through WQF (Weighted Fair Queuing) or Strict Priority Queuing (default)
-

VLAN Tagging

- Default – Transparent to VLAN frames
 - Enable discarding of tagged frames
 - Enable discarding of untagged frames
 - Untag – Removes any existing tag
 - Insert Tag – Insert (if original frame is untagged) or replace (if original frame is tagged) the VLAN ID and priority with the configured default VLAN ID and priority tag.
 - Insert Double tag (Q in Q) – Append an additional tag using the configured default VLAN ID and priority.
-

Unknown Multicast Frame filtering

When enabled, Multicast frames with an unknown destination address are not allowed to egress the port

Unknown Unicast Frame filtering

When enabled, Unicast frames with an unknown destination address are not allowed to egress the port

Unidirectional Ethernet

When enabled, provides the ability to restrict port to one-way traffic flow. Used in applications such as unidirectional video broadcasting as well as providing security for ethernet connections in accessible public areas

Configuration Mode selection

Select whether the module is to use the on-board DIP switches or enable the management module in the chassis to manage

Auto-MDIX

Can manually set Auto or MDIX on the copper port via on-board strap or via the management card. Auto-MDIX (automatic medium-dependant interface crossover) detects the signaling on the copper ethernet interface to determine the type of cable connected (straight-through or crossover) and automatically configures the connection when enabled. The media converter can also correct for wires swapped within a pair. The media converter will adjust for up to 120ns of delay skew between the 1000Base-T pairs.

Module Information

- Chassis slot number that the module is in
 - Media converter model and serial number
 - User configurable media converter module name
 - User configurable fiber port name
 - User configurable copper port name
 - Copper Downshift status
 - Hardware revision number
 - Firmware version number
-

Module DIP switch settings

View hardware DIP switch settings

Selectable Max Packet Size

Set max packet size to 1522 / 2048 or 10,240 (default)

10BaseT Extended Distance

Normal/extended – default Normal. By configuring as “extended”, the 10baseT receiver sensitivity is increased providing the possibility of an 10BaseT connection greater than 100m.

Auto Copper downshift

automatically detects a 2-pair cable environment and downshifts operation of the link to 100 Mb/s. Configure the number of times (0-8) that the PHY will attempt to establish a successful Gigabit link before attempting to “downshift” as an auto-negotiating 10/100 device. Setting # of attempts to 0 (default) disables the feature.

Virtual Cable Test

A test that enables the detection of potential copper cabling issues such as pair polarity pair swaps and excessive pair skew as well as any opens, shorts or any impedance mismatch. Will report the distance in the cable to the open or short.

Port Control

Enable or disable individual fiber or copper port on the module

Copper Port Status

- Port Enabled (Yes/No)
 - Link Status (Up/Down)
 - Auto Negotiation Settings (Disabled, Complete or In Progress)
 - Resolved as crossover MDI or MDIX type
-

Fiber Port Status

- Port Enabled (Yes/No)
 - Connector type (SC, LC, ST)
 - Link Status (Up/Down)
 - Far End Fault (OK, Failed)
 - Fiber Loopback mode (On/Off)
-

Module Control

- Reset card
 - Reset to factory default
 - Reset Statistical counters
 - Phy specific commands such write/read config, read dip switches
 - Update firmware
 - Fiber Loopback mode. (On/Off)
 - Virtual Cable Test. (On/Off)
 - Upload/download configuration
-

Backup and Restore

Provides fast and easy module replacement. Management module will always save a copy of the media converter configuration and will restore this configuration automatically to the media module when it is detected in the slot

Detailed port statistics

To assist in troubleshooting copper and fiber links, an extensive list of ingress and egress counters for both copper and fiber ports are available. These statistics can be viewed locally via the management module or from a central SNMP NMS on the network

Auto-Negotiation (802.3u)

The media converter supports auto negotiation. The 1000Base-X fiber interface negotiates according to 802.3 clause 37. The 10/100/1000Base-T negotiates according to 802.3 clause 28 and 40. The 1000Base-X will link up with its partner after the highest common denominator (HCD) is reached and the copper has linked up with its partner. The 1000Base-X will continue to cycle through negotiation transmitting a remote fault of offline (provided this is enabled through the switch setting) until the copper is linked up and the HCDs match.

The media converter supports auto-negotiation of full duplex, half duplex, remote fault, full duplex pause, asymmetric pause and Auto MDI-X.

Smart Link Pass-Through

When the Link Mode switch is placed into Smart Link Pass-Through mode, the copper ethernet port will reflect the state of the 1000Base-X media converter port. This feature can be used whether fiber auto-negotiation is enabled or disabled.

Fiber Fault Alert

With Fiber Fault Alert the state of the 1000Base-X receiver is passed to the 1000Base-X transmitter. This provides fault notification to the partner device attached to the 1000Base-X interface of the media converter. If the 1000Base-X transmitter is off as a result of this fault it will be turned on periodically to allow the condition to clear should the partner device on the 1000Base-X be using a similar technique. This eliminates the possibility of lockouts that occur with some media converters. Applies only when fiber auto-negotiation is disabled.

Pause (IEEE 802.3xy)

Pause signaling is an IEEE feature that temporarily suspends data transmission between two devices in the event that one of the devices becomes overwhelmed. The media converter supports pause negotiation on the 10/100/1000Base-T connection and 1000Base-X fiber connection.

Duplex

Full and half duplex operation supported.

Jumbo Packets

Transparent to jumbo packets up to 10KB.

Remote Loopback

Capable of performing a loopback on the 1000Base-X fiber interface.

Specifications	
Lifetime limited warranty	Reach, RoHS and WEEE Compliant HTSUS Number: 8517.62.0020 UNSPSC Code: 43201553 ECCN: 5A991
 	
Indicators	
Power / TST	This green LED is turned on when power is applied to the media converter. Otherwise it is off. The LED will blink when in Loopback test mode.
Fiber link on / Receive activity (LKF)	This green LED is operational only when power is applied. The LED is on when the 1000Base-X link is on and flashes with a 50% duty cycle when data is received.
Copper link on / Receive activity (LKC)	This green LED is operational only when power is applied. The LED is on when the 10/100/1000Base-T link is on and flashes with a 50% duty cycle when data is received.
Fiber Duplex (FDF)	This green LED is operational only when power is applied. The LED is on when the 10/100/1000Base-X link is operational in full duplex mode. The LED is off when in half duplex.
Copper Duplex (FDC)	This green LED is operational only when power is applied. The LED is on when the 10/100/1000Base-T link is operational in full duplex mode. The LED is off when in half duplex.
10/100/1000 Speed	This multi-color LED is operational only when power is applied. The LED is green when the speed of the copper ethernet port is running at 1000 Mbps. The LED is orange when the speed of the copper Ethernet port is running at 100 Mbps. The LED is off when in 10 Mbps.

Switches: On-Board (If Auto/Switch strap is set to Switch)	
Auto-Negotiation (802.3u)	• <i>Enabled (Default)</i> - The media converter uses 802.3u Auto-negotiation on the 10/100/1000Base-T interface. It is set to advertise full duplex, half duplex, pause and remote fault capabilities. • <i>Disabled</i> - The media converter sets the port according to the position of the speed and duplex switches.
Link Mode	Link Mode provides a transparency to the state of the copper link allowing for simplified trouble shooting from the devices connected to the media converter. <i>Normal (Default — Up)</i> • With Fiber Auto Negotiation enabled when the copper link goes down the 1000Base-X link is brought down. The 1000Base-X link will advertise Remote Fault (Link Fault). • With Fiber Auto Negotiation disabled the state of the copper link has no effect on the 1000Base-X link. <i>Smart Link Pass Through (Down)</i> • With Fiber Auto Negotiation enabled the behavior is as follows. When the copper link goes down the 1000Base-X link is brought down. The 1000Base-X link will advertise Remote Fault (Link Fault). When Remote Fault (Link Fault) is received on the 1000Base-X interface the copper transmitter will be turned off. When the copper receiver is off the 1000Base-X transmitter will be turned off. When the 1000Base-X receiver goes off the copper transmitter will be turned off. • With Fiber Auto-Negotiation disabled the behavior is as follows. When the copper receiver is off the 1000Base-X transmitter will be turned off. When the 1000Base-X receiver goes off the copper transmitter will be turned off.
Fiber Fault Alert	The Fiber Fault Alert switch has meaning when Auto-Negotiation is disabled • <i>Enabled (Default - Up)</i> When the 1000Base-X receiver is off the 1000Base-X transmitter is turned off. Periodically the 1000Base-X receiver will be turned on for a short period to allow the condition to clear if the 1000Base-X link partner is using a similar feature. • <i>Disabled (Down)</i>

Remote Loopback	The media converter can perform a loopback on the 1000Base-X fiber interface. • <i>Disabled (Default - Up)</i> • <i>Enabled</i> - The 1000Base-X receiver is looped to the 1000Base-X transmitter. The copper transmitter is taken off the interface.
Auto-MDIX (Strap)	If Auto-Negotiation (802.3u) is enabled, the media converter determines the current cable pinout to use on the copper interface. If Auto-Negotiation (802.3u) is disabled the Media converter will use the RX Energy method on the copper interface to set the port MDI or MDIX whichever is appropriate. • <i>Enabled (Default)</i> - Either a straight-through or crossover type cable can be used to connect the media converter to the device on the other end of the cable. • <i>Disabled</i> - If the partner device on the other end of the cable does not have the Auto-MDIX feature a specific cable, either a straight-through or crossover will be required to ensure that the media converter's transmitter and the partner devices transmitter are connected to the others receiver. The Media converter's 100Base-TX port is configured as MDI-X with this switch setting.
Speed Copper	• 100 (Default) • 10
Duplex Copper	• Full (Default) • Half
Duplex Fiber	• Full (Default) • Half
Connectors	
10/100/1000Base-T	RJ45 connector • 2 pair CAT5, EIA/TIA 568A/B or better cable for 10/100. • 4 pair CAT5 UTP cable for Gigabit.
Magnetic Isolation	1.5kv
Filtering	
Filtering	1024 MAC Addresses

Frame Specifications	
Buffer	1000 Kbits frame buffer memory
Size	• Maximum frame size of 10,240 bytes -- Gigabit • Maximum frame size of 2048 bytes -- Fast Ethernet
Environmental Specifications	
Operating Temperature	0°C to 50°C (32°F to 122°F)
Storage Temperature	minimum range of -25°C to 70°C (-13°F to 158°F)
Operating Humidity	5% to 90% non-condensing
Storage Humidity	5% to 95% non-condensing
Operating Altitude	Up to 3,048 meters (10,000 feet)
Heat Output (BTU/HR)	7.2
Maximum Power Consumption (Watts)	2.1
MTBF (Hours)*	598,000 Hours <i>Calculation model based on MIL-HDBK-217-FN2 @ 30°C</i>
Mechanical - Hot Swapping Card	
Edge Connector	32 pin DIN 41612 / IEC 60603-2 Type B/2 Male. First make, last break for ground and power
Card insertion and removal	Captive thumb screws enable fast insertion and removal. Can be further tighten with a screwdriver.
Product Weight	
Weight	0.15 kg, 0.33 lbs
Packaging	
Shipping Weight	0.33 kg, 0.73 lbs
Shipping Dimensions	203 x 38 x 152 mm, 8 x 1.5 x 6 inches

Regulatory Approvals	
Emissions	• FCC Part 15 Class A • CISPR 32 / EN 55032 • EN61000-3-2
Immunity	CISPR 35 / EN 55035
Electrical Safety	• UL/EN/IEC 62368-1 • CAN/CSA C22.2 No. 62368-1 • UL 60950-1 • IEC 60950-1(ed 2); am1, am2 • EN 60950-1:2006+A11:2009+A1:2010+A12:2011+A2:2013 • CE
Laser Safety	• EN 60825-1 • Fiber optic transmitters on this device meet Class 1 Laser safety requirements per IEC-60825 FDA/CDRH standards and comply with 21CFR1040.10 and 21CFR1040.11.

Product List



CM-1110-S2ST160 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-ZX 1550 nm single mode (ST) [160 km/100 miles]. Managed or unmanaged operation

Part Number(s)

05052890



CM-1110-M2SC05 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-SX 850nm multimode (SC) [550 m/1804 ft.]. Managed or unmanaged operation

Part Number(s)

05052600



CM-1110-M2LC05 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-SX 850nm multimode (LC) [550 m/1804 ft.]. Managed or unmanaged operation

Part Number(s)

05052610



CM-1110-M2ST05 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-SX 850nm multimode (ST) [550 m/1804 ft.]. Managed or unmanaged operation

Part Number(s)

05052710



CM-1110-M2SC2 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-LX 1310nm Extended multimode (SC) [2km /6562 ft.]. Managed or unmanaged operation

Part Number(s)

05042970



CM-1110-M2LC2 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-LX 1310nm Extended multimode (LC) [2km /6562 ft.]. Managed or unmanaged operation

Part Number(s)

05042990



CM-1110-M2ST2 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-LX 1310nm Extended multimode (ST) [2km /6562 ft.]. Managed or unmanaged operation

Part Number(s)

05042980



CM-1110-S2SC10 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-LX/LH 1310 nm single mode (SC) [10 km/6.2 miles] or multimode (SC) [550 m/1804 ft.] using a mode

Part Number(s)

05052630



CM-1110-S2LC10 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-LX/LH 1310 nm single mode (LC) [10 km/6.2 miles] or multimode (LC) [550 m/1804 ft.] using a mode

Part Number(s)

05052620



CM-1110-S2ST10 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-LX/LH 1310 nm single mode (ST) [10 km/6.2 miles]. Managed or unmanaged operation

Part Number(s)

05052720



CM-1110-S2SC40 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-EX 1310 nm single mode (SC) [40 km/24.9 miles]. Managed or unmanaged operation

Part Number(s)

05052690



CM-1110-S2LC40 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-EX 1310 nm single mode (LC) [40 km/24.9 miles]. Managed or unmanaged operation

Part Number(s)

05052640



CM-1110-S2ST40 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-EX 1310 nm single mode (ST) [40 km/24.9 miles]. Managed or unmanaged operation

Part Number(s)

05052730



CM-1110-S2SC70 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-ZX 1550 nm single mode (SC) [70 km/43.5 miles]. Managed or unmanaged operation

Part Number(s)

05052650



CM-1110-S2LC70 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-ZX 1550 nm single mode (LC) [70 km/43.5 miles]. Managed or unmanaged operation

Part Number(s)

05052660



CM-1110-S2ST70 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module.
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-ZX 1550 nm single mode (ST) [70 km/43.5 miles]. Managed or unmanaged operation

Part Number(s)

05052740



CM-1110-S2SC120 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-EZX 1550 nm single mode (SC) [120 km/74.6 miles] Managed or unmanaged operation

Part Number(s)

05052760



CM-1110-S2LC120 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-EZX 1550 nm single mode (LC) [120 km/74.6 miles] Managed or unmanaged operation

Part Number(s)

05052770



CM-1110-S2SC160 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-ZX 1550 nm single mode (SC) [160 km/100 miles]. Managed or unmanaged operation

Part Number(s)

05052910



CM-1110-S2LC160 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-ZX 1550 nm single mode (LC) [160 km/100 miles]. Managed or unmanaged operation

Part Number(s)

05052920



CM-1110-S2ST120 - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module
10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-EZX 1550 nm single mode (ST) [120 km/74.6 miles] Managed or unmanaged operation

Part Number(s)

05052750



CM-1110-M1SC05U - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000BASE-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1310nm TX / 1550nm RX single strand fiber, multimode (SC) [550 m/1804 ft]. Managed or unmanag

Part Number(s)

05042870



CM-1110-M1SC05D - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000BASE-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1550nm TX / 1310nm RX single strand fiber, multimode (SC) [550 m/1804 ft]. Managed or unmanag

Part Number(s)

05042860



CM-1110-S1SC10U - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1310nm TX / 1490nm RX single strand fiber, single mode (SC) [10 km/6.2 miles]. Managed or un

Part Number(s)

05052670



CM-1110-S1SC10D - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1490nm TX / 1310nm RX single strand fiber, single mode (SC) [10 km/6.2 miles]. Managed or un

Part Number(s)

05052680



CM-1110-S1SC20U - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1310nm TX / 1490nm RX single strand fiber, single mode (SC) [20 km/12.4 miles]. Managed or u

Part Number(s)

05052930



CM-1110-S1SC20D - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1490nm TX / 1310nm RX single strand fiber, single mode (SC) [20 km/12.4 miles]. Managed or u

Part Number(s)

05052940



CM-1110-S1SC40U - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1310nm TX / 1490nm RX single strand fiber, single mode (SC) [40 km/25 miles]. Managed or unm

Part Number(s)

05052950



CM-1110-S1SC40D - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1490nm TX / 1310nm RX single strand fiber, single mode (SC) [40 km/25 miles]. Managed or unm

Part Number(s)

05052960



CM-1110-S1SC80U - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1510nm TX / 1590nm RX single strand fiber, single mode (SC) [80 km/50 miles]. Managed or unmanaged

Part Number(s)

05052970



CM-1110-S1SC80D - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1590nm TX / 1510nm RX single strand fiber, single mode (SC) [80 km/50 miles]. Managed or unmanaged

Part Number(s)

05052980



CM-1110-S1SC120U - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1510nm TX / 1590nm RX single strand fiber, single mode (SC) [120 km/75 miles]. Managed or unmanaged

Part Number(s)

05052990



CM-1110-S1SC120D - 10/100/1000 Gigabit Ethernet Media and Rate Converter Managed Module. 10/100/1000Base-T (RJ-45) [100 m/328 ft.] to 1000Base-BX 1590nm TX / 1510nm RX single strand fiber, single mode (SC) [120 km/75 miles]. Managed or unmanaged

Part Number(s)

05052590