

ePMP™ 3000L Access Point



Cambium Networks' ePMP product line has set the standard for high performance, scalability and reliability in harsh interference environments all at a compelling price. The ePMP 3000L is the third generation access point (AP) that carries on the interference tolerance mechanisms with an emphasis on high-performance in low-density point to multipoint sectors. The ePMP 3000L is a 2X2 MIMO connectorized access point that can support a wide variety of deployments including 90/120 degree sectors, narrow-sector horns or even 360 degree omni coverage. In addition, the ePMP 3000L continues interference mitigation techniques with support of TDD synchronization using GPS and the robust software from the ePMP product line. The ePMP 3000L AP system consists of the ePMP 3000L AP, an optional 2X2 sector antenna and a wide variety of subscriber modules with varying form factors and link budgets.

The ePMP 3000L system boasts high packet per second performance, peak throughput of 600 Mbps and supports subscriber modules with up to 600 Mbps of peak throughput.

KEY ADVANTAGES:

- **MicroPOP Applications:** ePMP 3000L is ideally suited for areas with low density or small numbers of subscribers. With support for narrow-band sectors and omnis, coverage can be added exactly where needed.
- **Frequency Reuse:** Supports GPS synchronization and SM Transmit power control to allow for frequency re-use.
- **Unmatched Performance and Scalability:** With the efficient Cambium Networks MAC protocol and advanced air-fairness scheduler the ePMP 3000L supports high performance and low consistent latency to subscribers.

KEY SPECIFICATIONS:

- 2X2 MIMO support with peak throughput of 600 Mbps
- 256QAM-5/6, 80 MHz support
- Supports a wide frequency range: 4910 to 5950 MHz
- 802.3at compliant 100/1000BaseT interface
- Frequency re-use with GPS sync and interference mitigation
- Connectorized for use with sector antenna. Also compatible with RF Elements Twistport(tm) Adaptor for ePMP
- Cloud or on-premises network management with cnMaestro

SPECIFICATIONS

PRODUCT

Model/Part #	See table below for full set of Model and Part Numbers
--------------	--

SPECTRUM

Channel Spacing	Configurable on 5 MHz increments
Frequency Range	4910 - 5950 MHz (exact frequencies as allowed by local regulations)
Channel Width	20 40 80 MHz

INTERFACE

MAC (Media Access Control) Layer	Cambium Proprietary
Physical Layer	2X2 MIMO/OFDM
Ethernet Interfaced	100/1000BaseT, rate auto negotiated, 802.3at compliant & Aux SFP port
Powering Methods Supported	56 V PoE (included), standard 802.3at PoE Supply, or CMM5 with 56 V and 5 pin to 7 pin cross over cable adapter
Protocols Used	IPv4/IPv6 , UDP, TCP, IP, ICMP, SNMPv2c, HTTPs, STP, SSH, IGMP Snooping
Network Management	HTTPS, SNMPv2c, SSH
VLAN	802.1Q with 802.1p priority

PERFORMANCE

ARQ	Yes
Nominal Receive Sensitivity (w/FEC) @20 MHz Channel	MCS0 = -89 dBm to MCS8 (256 QAM-3/4) = -66 dBm (per chain)
Nominal Receive Sensitivity (w/FEC) @40 MHz Channel	MCS0 = -87 dBm to MCS9 (256QAM-5/6) = -64 dBm (per chain)
Nominal Receive Sensitivity (w/FEC) @80 MHz Channel	MCS0 = -84 dBm to MCS9 (256QAM-5/6) = -59 dBm (per chain)
Modulation Levels (Adaptive)	MCS0 (BPSK) to MCS 9 (256 QAM 5/6)
GPS Synchronization	Yes, via Internal GPS or Cambium Sync (Internal GPS receiver also contains a patch antenna and can be used without the external puck antenna)
Quality of Service	Three level priority (Voice, High, Low) with packet classification by DSCP, COS, VLAN ID, IP & MAC Address, Broadcast, Multicast and Station Priority, MIR/CIR support*

LINK BUDGET

Antenna	90/120 Degree 2X2 Sector Antenna (C050900D021A) Available
Transmit Power Range	0 to +29 dBm (combined, to regional EIRP limit) (1 dB interval)

PHYSICAL

Sector Antenna Connection	2 x 50 ohm, RP (Reverse Polarity) SMA Also compatible with RF Elements Twistport™ Adaptor for ePMP
GPS Antenna Connection	1 x 50 ohm, RP (Reverse Polarity) SMA
Surge Suppression	1 Joule Integrated. C000000L033A - 56V Gigabit surge suppressor recommended for optimal surge protection
Environmental	IP67
Temperature	-22°F to +140°F (-30°C to +60°C)
Power Consumption	12 Watts
Input Voltage	30 Volts Nominal (14V to 30V Range)
Weight	0.7 kg (1.5 lbs) without brackets
Dimensions (L x W x H)	22.2 x 12.4 x 4.5 cm (8.75 x 4.9 x 1.75 in) without brackets

Note:

* Items marked with asterix are planned for a future release

SPECIFICATIONS

SECURITY

Encryption	128 bit AES (CCMP mode)
------------	-------------------------

CERTIFICATIONS

FCCID	Z8H-89FT0047**
-------	----------------

INDUSTRY CANADA	109W-0047
-----------------	-----------

CE	EN 301 893 V2.1.1 (5.4 GHz), EN 302 502 V2.1.1 (5.8 GHz)**
----	--

**Certifications are a place holder until official grant is given

TABLE OF PART NUMBERS

PART NUMBER**DESCRIPTION**

C058910A122A	ePMP 3000L 5 GHz Access Point Radio (FCC) (US cord)
C050910A124A	ePMP 3000L 5 GHz Access Point Radio (IC) (Canada/US cord)
C050910A223A	ePMP 3000L 5 GHz Access Point Radio (EU) (EU cord)
C050910A323A	ePMP 3000L 5 GHz Access Point Radio (EU) (UK cord)
C050910A021A	ePMP 3000L 5 GHz Access Point Radio (ROW) (no cord)
C050910A121A	ePMP 3000L 5 GHz Access Point Radio (ROW) (US cord)
C050910A221A	ePMP 3000L 5 GHz Access Point Radio (ROW) (EU cord)
C050910A321A	ePMP 3000L 5 GHz Access Point Radio (ROW) (UK cord)
C050910A421A	ePMP 3000L 5 GHz Access Point Radio (ROW) (India cord)
C050910A422A	ePMP 3000L 5 GHz Access Point Radio (India) (India Cord)
C050910A521A	ePMP 3000L 5 GHz Access Point Radio (ROW) (China cord)
C050910A621A	ePMP 3000L 5 GHz Access Point Radio (ROW) (Brazil cord)
C050910A721A	ePMP 3000L 5 GHz Access Point Radio (ROW) (Argentina cord)
C050910A821A	ePMP 3000L 5 GHz Access Point Radio (ROW) (ANZ cord)
C050910A921A	ePMP 3000L 5 GHz Access Point Radio (ROW) (South Africa cord)
C050910AZ21A	ePMP 3000L 5 GHz Access Point Radio (ROW) (No PSU)